



NetWyl Informatik
IT-Security Experts

Checkpoint Restoring Factory Defaults

Version 1.0


Dokument Name: Checkpoint_Restoring Factory Defaults

Version	Datum	Änderungsnotiz	Betroffene Seiten	Status	Author
1.0	10.07.2024				

Copyright 2024 NetWyl Informatik

NetWyl Informatik GmbH
Täschmattstrasse 19
6015 Luzern
info@netwyl-informatik.ch
Phone: +41 41 520 73 90

If necessary, restore the appliance to its factory default settings.



Restoring from the Gaia Portal

Use the Gaia Portal to restore the appliance to the factory default settings.

To restore a Gaia appliance from the Gaia Portal:

1. In your web browser, connect to the management IP address:
https://<appliance_ip_address>
2. Log in to the Gaia Portal of the appliance with the administrator username and password.
3. In the left navigation tree, click Maintenance > Factory Defaults.
The Factory Defaults window opens. The image installed on the appliance is shown.
4. Click Apply.
The appliance reboots and installs the selected version from scratch.

Restoring from the Boot Menu

To restore the appliance from the Boot Menu:

1. Connect the supplied serial cable's RJ45 or USB type-C connector to the console port on the front of the appliance.
2. From the computer, open a terminal emulation program such as PuTTY or Microsoft HyperTerminal.
3. Configure the terminal emulation program:
 - In PuTTY select the Serial connection type.
 - In the HyperTerminal Connect To window, select a port from the Connect using list.
 - Define the serial port settings:
9600 BPS, 8 bits, no parity, 1 stop bit
 - From the Flow control list, select None.
 - Connect to the appliance.
 - Reboot or turn on the appliance.

The appliance initializes and status messages are shown in the terminal emulation program.

- When the message "Press any key to see the boot menu" is shown, you have approximately four seconds to hit any key to activate the Boot menu.

- From the Boot menu, select the relevant Reset to factory defaults image.
- Press Enter.

The appliance initializes and status messages are shown in the terminal emulation program.

Restoring from Gaia Clish

To restore the appliance from Gaia Clish:

1. Connect to the command line on the appliance.
2. Log in to Gaia Clish.
3. Run:

```
set fcd revert <image_name>
```

Example:

```
MyAppliance> set fcd revert Gaia_R80.30
```

Warning! This command will erase all the current configuration on this appliance and will revert it to the selected image.

```
Are you sure you want to continue such action? (Yes/No) [No]yes Reverting to factory defaults  
Gaia_R80.30
```

```
MyAppliance>Broadcast message from admin (Tue May 14 12:19:16 2019):The system is going  
down for reboot NOW!
```

```
INIT: Sending processes the TERM signal
```

```
x
```